

Dual Socket AC EV Charger

7.4kW_{x2} / 22kW_{x2}

Logo

LCD Screen

RFID

LED Light

Emergency
Button SwitchElectric Leakage
Test Button

Type 2 Socket



Product Overview

Elevate your charging experience with the Beny Dual Socket AC EV charger, certified by reputable associations. It's engineered for intelligence, reliability, convenience, and efficiency. Take charge of your charger through a smart app and multiple connectivity options. Enjoy seamless interaction with a 5.0-inch touch screen interface.

Product Advantages

5.0-inch
Touch ScreenWi-Fi/Ethernet
/Bluetooth/4GDLB and Solar
Compatible





IP55 Rating



OCPP 1.6J

Full
Protection

Model Selection

| Dual Socket AC EV Charger | BCPC-B2N-P | BCPC-BT2N-P | BCPC-D2N-P | BCPC-DT2N-P |
|--|---|---|---|---|
| |  |  |  |  |
| Maximum Power | 7.4kW | 22kW | 2x7.4kW | 2x22kW |
| Input Voltage /Output voltage | AC230 1-Phase | AC400 3-Phase | AC230 1-Phase | AC400 3-Phase |
| Input Frequency | 50/60Hz | | | |
| Tethered/Socket | Socket | | | |
| Meter | MID Meter | | 2xMID Meter | |
| Display | LCD Screen+LED Lights | | | |
| RFID | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| DLB | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> |
| Wi-Fi | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Ethernet | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Bluetooth | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| 4G | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> |
| Over Voltage &Under Voltage Protection | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Emergency Stop | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Over Current Protection | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| CP Signal Short Circuit Protection | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Over Temperature Protection | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Lightning Protection | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Contactor Adhesion Protection | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Protection Degree | IP55 | IP55 | IP55 | IP55 |
| Environment Temperature | -25°C~+50°C | | | |
| Maximun Altitude | <2000m | | | |

✓ : Standard ○ : Optional

